

(2) A frequency meter with a selector switch to connect the meter to each generator.

(3) An exciter field rheostat.

(f) For each shore power connection each switchboard must have:

(1) A circuit breaker or fused switch;

(2) A pilot light connected to the shore side of the circuit breaker or fused switch; and

(3) One of the voltmeters under paragraph (b)(5) of this section connected to show the voltage of each phase of the shore power connection.

(g) The equipment under paragraphs (b), (d), (e), and (f) of this section, except the equipment under paragraphs (b)(1), (b)(2), and (f)(1), must be on the ship's service switchboard or on a central control console that:

(1) Is in the same control area as the main ship's service switchboard or can remotely control the ship's service generator circuit breaker;

(2) Has a generator section that has only generator functions;

(3) Has the generator section segregated from each other console section by a fire-resistant barrier; and

(4) Has cabling from the main switchboard to the generator section of the console that:

(i) Has only generator control and generator instrumentation circuits; and

(ii) Is protected from mechanical damage.

§ 111.30-27 Direct current ship's service switchboards.

(a) Each direct current ship's service switchboard must have the equipment required by paragraphs (b) through (f) of this section.

(b) For each connected generator, each switchboard must have the following:

(1) A circuit breaker that meets § 111.12-11 and § 111.50-5.

(2) A disconnect switch or link for each generator conductor, except a switchboard having a draw-out or plug-in type generator circuit breaker that disconnects—

(i) Each conductor; or

(ii) If there is a switch in the generator neutral, each ungrounded conductor.

(3) A field rheostat.

(4) A pilot lamp connected between the generator and circuit breaker.

(c) For each two-wire generator, each switchboard must have:

(1) An ammeter; and

(2) A voltmeter with a selector switch that connects the voltmeter to show:

(i) Generator voltage; and

(ii) Bus voltage.

(d) For each three-wire generator, each switchboard must have the following:

(1) An ammeter for:

(i) The positive lead; and

(ii) The negative lead.

(2) A center zero type ammeter for the neutral ground connection.

(3) A voltmeter with a selector switch that connects the voltmeter to show generator and bus voltage:

(i) Positive to negative;

(ii) Positive to neutral; and

(iii) Neutral to negative.

(e) Each switchboard must have ground detection that meets Subpart 111.05 for the:

(1) Main power system;

(2) Main lighting system; and

(3) Emergency lighting system.

(f) For each shore power connection, each switchboard must have:

(1) A circuit breaker or fused switch; and

(2) A pilot light connected to the shore side.

(g) One of the voltmeters under paragraph (c)(2) or (d)(3) of this section must be connected to show:

(1) For each two-wire system, shore connection voltage; and

(2) For each three-wire system, shore connection voltage:

(i) Positive to negative;

(ii) Positive to neutral; and

(iii) Neutral to negative.

§ 111.30-29 Emergency switchboards.

(a) Each emergency generator must have an emergency switchboard.

(b) There must be a test switch at the emergency switchboard to simulate a failure of the normal power source and cause the emergency loads to be supplied from the emergency power source.

(c) The emergency switchboard must be as near as practicable to the emergency power source but not in the same

§ 111.33-1

space as a battery emergency power source.

(d) Each alternating-current emergency switchboard must have the equipment required by paragraphs (c) through (e) of this section.

(e) For each connected emergency generator, each emergency switchboard must have:

(1) A circuit breaker that meets § 111.12-11;

(2) A disconnect switch or link for each emergency generator conductor, except for a switchboard with a draw out or plug-in type generator circuit breaker that disconnects:

(i) Each generator conductor; and

(ii) If there is a switch in the generator neutral, each ungrounded conductor; and

(3) A pilot lamp connected between the generator and circuit breaker.

(f) For each emergency generator that is not excited from a variable voltage or rotary amplifier exciter that is controlled by a voltage regulator unit acting on the exciter field, each emergency switchboard must have:

(1) A generator field rheostat;

(2) A double pole field switch;

(3) Discharge clips; and

(4) A discharge resistor.

(g) Each emergency switchboard must have the following:

(1) An ammeter with a selector switch that connects the ammeter to show the current for each phase.

(2) A voltmeter with a selector switch that connects the voltmeter to show:

(i) Generator voltage of each phase; and

(ii) Bus voltage of one phase.

(3) Ground detection that meets subpart 111.05 for the emergency lighting system.

(4) A frequency meter.

(5) An exciter field rheostat.

(6) A voltage regulator and a voltage regulator functional cut-out switch.

(h) Each direct-current emergency switchboard must have the:

(1) Equipment under § 111.30-27 (b) through (d); and

46 CFR Ch. I (10-1-06 Edition)

(2) Ground detection under subpart 111.05 for the emergency lighting system.

[CGD 74-125A, 47 FR 15236, Apr. 8, 1982, as amended by CGD 94-108, 61 FR 28279, June 4, 1996]

Subpart 111.33—Power Semiconductor Rectifier Systems

§ 111.33-1 General.

This subpart is applicable to all power semiconductor rectifier systems. In addition to the regulations contained in this subpart, the requirements of §§ 111.30-11, 111.30-19 and 111.30-21 of this part must be met, if applicable.

§ 111.33-3 Nameplate data.

(a) Each semiconductor rectifier system must have a nameplate of durable material affixed to the unit that meets the requirements of—

(1) Section 45.11 of IEEE Std 45; or

(2) IEC 92-304 (clause 8).

(b) Each semiconductor rectifier system must have a nameplate containing the words "marine semiconductor rectifier," and the following information:

(1) Manufacturer's name and address.

(2) Manufacturer's serial number.

(3) Type.

(4) Rated AC volts.

(5) Rated AC amperes.

(6) Number of phases.

(7) Frequency.

(8) Rated DC volts.

(9) Rated DC amperes.

(10) Ambient temperature range.

(11) Duty cycle.

(12) Cooling medium.

(c) If, on small rectifiers, the information required by paragraph (a) of this section cannot be shown because of space limitations, the nameplate must be at least large enough to contain the manufacturer's name and serial number. The remaining information must be shown on the schematic diagram.

[CGD 74-125A, 47 FR 15236, Apr. 8, 1982, as amended by CGD 94-108, 61 FR 28279, June 4, 1996]