



RECORDING AND SENDING

Creating a new voice message

- ▶ From the main menu 2
- ▶ Record message
- ▶ When finished #
- ▶ Enter destinations (Press # to spell name)
- or
- ◊ ▶ When finished entering all destinations #-#
- ▶ Specify delivery options (see below)
- ▶ Send #

TIPS:

- To erase and rerecord *
- If you don't know the mailbox number, # to spell last name Q = 7 Z = 9

Specifying delivery options

- Private 1
- Urgent 2
- Future delivery 4
- ◊ Review destination list 5

LISTENING AND RESPONDING

Reviewing voice messages

- From the main menu ■

TIPS:

- Use playback controls during message play
- Skip to next message #
- Skip to next queue #-#

Replying to a message

- ▶ At end of message 8
- ▶ Record reply
- ▶ When finished #
- ▶ Send #

Replying by calling the sender

- ▶ At end of message 8-8
- ▶ System dials sender's phone number

TIP:

- You cannot reply to messages from outside callers.

Sending a copy

- ▶ At end of message 6
- ▶ Record introduction
- ▶ When finished #
- ▶ Enter mailbox number
- ▶ Send #

RECEIVING FAX MESSAGES

Printing a fax sent to your mailbox

- ▶ From the main menu 1
- ▶ Print 2
- ▶ Choose:
 - Primary destination 1
 - Alternate destination 2
 - Current location 3

Setting or changing your primary fax destination

- ▶ From the main menu -2-2-1

Telling the system to auto print or not print each fax to the primary destination as soon as it is received

- 2-2-2

LOCATING MESSAGES

Locating messages you have sent

- ▶ From the main menu 3-1

Locating message you have received

- ▶ From the main menu 3-2
- ▶ Choose source:
 - From specific user 1
 - From all outside callers 2
 - From specific outside callers 3

SETTING OUTCALL NOTIFICATION

Controlling when the message server outcalls to you with notification that you have messages

- ▶ From the main menu 4-1
- ▶ Choose one:
 - Do call 1
 - Do not call 2

Setting up your outcall notification schedule

- ▶ From the main menu 4-4

TIP:

- When you enter the telephone number, include area code if different from that of your message server.

PERSONALIZING YOUR MAILBOX

Changing your passwords—do it frequently

- ▶ From the main menu -2-1-1

Recording personal greeting

- ▶ From the main menu 4-3-1-2

Recording extended absence greeting

- ▶ From the main menu -3-2

Using group distribution lists—15 lists, up to 250 members total

- ▶ From the main menu 4-2-1-2
- ▶ Choose action:
 - Create 1
 - Edit 2
 - Delete 3

GENERAL TIPS

Press the wrong key?

- Cancel or back up *

Need help?

- Not sure which key to press 0
- Talk to attendant (only at Main Menu) 0-0

Go back to the main menu?

- Repeat * until you hear prompts for reviewing and sending messages

Other tips and shortcuts

- Bypass message server greeting #
- If prompted to press a key twice, be sure to do it closely together



ARIA User Interface on INTUITY Messaging Solutions AT-A-GLANCE

◊ Enhanced Addressing Mode (optional feature) only

Lucent Technologies

1001 Murphy Ranch Road
Milpitas, CA, USA 95035-7912
<http://www.lucent.com>

©Copyright 1999 Octel Communications Corporation, a subsidiary of Lucent Technologies. All rights reserved. All trademarks identified by ® and ™ are registered trademarks or trademarks respectively, of Octel Communications Corporation, a subsidiary of Lucent Technologies. All other trademarks are the properties of their respective owners.
Printed in USA.
06/1999
Doc. #: 585-313-715
Comcode: 108455304
Issue: 1

THE POWER OF MESSAGING

Messaging gives you the ability to communicate effectively from any touchtone phone 24 hours a day, with one person or many. We want you to be familiar with the INTUITY messaging server as soon as possible, so you can put it to work for you. This guide explains a few of the system's important features. For more information, refer to the Aria User Interface on INTUITY Messaging Solutions User Reference Guide.

TIPS: • Before you reach your mailbox, you may hear some special system messages. You should listen to these messages before you proceed.

- Depending on the way your system is set up, some features may not be available to you, and you will not be prompted for those options.

ENTERING THE SYSTEM

From your office phone

- Call the internal INTUITY Message Server system number
- Enter your password

When away from your desk

- Call the INTUITY Message Server system number
- Press # to indicate you are a user
- Enter your mailbox number
- Enter your password



Lucent Technologies
Bell Labs Innovations

ARIA USER INTERFACE ON INTUITY MESSAGING SOLUTIONS AT-A-GLANCE

