

§ 129.315

(i) Any system identified as a vital system in §128.130(a) of this subchapter.

(ii) Interior lights.

(iii) Communication systems.

(iv) Navigational equipment and lights.

(v) Fire-protection equipment.

(2) A vessel with batteries of enough capacity for 3 hours of continuous operation to supply the loads specified in paragraph (a)(1) of this section, and with a generator or alternator driven by a propulsion engine, complies with paragraph (a)(1) of this section.

(b) Where a generator driven by a propulsion engine is used as a source of electrical power, no speed change, throttle movement, or change in direction of the propeller shaft of the vessel may interrupt power to any of the loads specified in paragraph (a)(1) of this section.

§ 129.315 Power sources for OSVs of 100 or more gross tons.

(a) The requirements of this section apply instead of those in subpart 111.10 of this chapter.

(b) If a generator provides electrical power for any system identified as a vital system by §128.130(a) of this subchapter, at least two power-generating sets must be provided. At least one set must be independent of the main propulsion plant. A generator not independent of the main propulsion plant must comply with §111.10-4(d) of this chapter. With any one generating set stopped, the remaining set or sets must provide the power necessary for the loads required by this section.

§ 129.320 Generators and motors.

(a) Each generator and motor, except a submersible-pump motor, must be—

(1) In an accessible space, adequately ventilated and as dry as practicable; and

(2) Mounted above the bilges to avoid damage by splash and to avoid contact with low-lying vapors.

(b) Each generator and motor must be designed for an ambient temperature of 50 °C (122 °F), except that—

(1) If the ambient temperature, in the space where a generator or motor is, does not exceed 40 °C (104 °F) under normal operating conditions, the gener-

46 CFR Ch. I (10-1-02 Edition)

ator or motor may be designed for an ambient temperature of 40 °C (104 °F); and

(2) A generator or motor designed for an ambient temperature of 40 °C (104 °F) may be used in a location where the ambient temperature is 50 °C (122 °F), if the generator or motor is derated to 80 percent of the full-load rating and if the rating or setting of the overcurrent devices of the generator or motor is reduced accordingly.

(c) For each generator rated at 50 volts or more, a voltmeter and an ammeter used for measuring voltage and current while the generator is in operation must be provided. For each alternating-current generator, a means for measuring frequency must also be provided. To ensure satisfactory operation of each generator, additional control equipment and measuring instruments, if needed, must also be provided.

(d) Each generator must have a nameplate attached to it indicating—

(1) Name of manufacturer, type of generator, and designation of frame;

(2) Output in kilowatts, or horsepower rating;

(3) Kind of rating (continuous, overload, or other);

(4) Amperes at rated load, voltage, and frequency;

(5) Number of phases, if applicable;

(6) Type of windings, if DC;

(7) When intended for connection in a normally grounded configuration, the grounding polarity; and

(8) For a generator derated to comply with paragraph (b)(2) of this section, the derated capacity.

(e) Each motor must have attached to it a nameplate containing the information required by Article 430 of NFPA 70.

§ 129.323 Multiple generators.

If an OSV uses two or more generators to supply electricity for the ship's service loads, to comply with §129.310(a) of this subpart, the following requirements must be met:

(a) Each generator must have an independent prime mover.

(b) The circuit breaker of a generator to be operated in parallel with another generator must comply with §§111.12-11(f), 111.30-19(a), and 111.30-25(d) of this chapter.

(c) The circuit breaker of a generator not to be operated in parallel with another generator must be interlocked to prevent that generator from being connected to the switchboard simultaneously with another.

§ 129.326 Dual-voltage generators.

If a dual-voltage generator is installed on an OSV—

(a) The neutral of the dual-voltage system must be solidly grounded at the switchboard's neutral bus and be accessible for checking the insulation resistance of the generator; and

(b) Ground detection must be provided that—

(1) For an alternating-current system, complies with §111.05-27 of this chapter; and

(2) For a direct-current system, complies with §111.05-29 of this chapter.

§ 129.330 Distribution panels and switchboards.

(a) Each distribution panel or switchboard must be in a location as dry as practicable, accessible, adequately ventilated, and protected from falling debris and dripping or splashing water.

(b) Each distribution panel or switchboard must be totally enclosed and of the dead-front type.

(c) Each switchboard must have non-conductive handrails.

(d) Each switchboard or main distribution panel must be fitted with a dripshield, unless the switchboard or distribution panel is of a type mounted deck-to-overhead and is not subject to falling objects or liquids from above.

(e) Each distribution panel and switchboard accessible from the rear must be constructed to prevent a person's accidental contact with energized parts.

(f) Working space must be provided around each main distribution panel and switchboard of at least 610 millimeters (24 inches) in front of the switchboard and, of at least 460 millimeters (18 inches) from the nearest bulkhead, stiffener, or frame behind the switchboard. Rear access is prohibited when the working space behind the switchboard is less than 460 millimeters (18 inches).

(g) Nonconductive mats or grating must be provided on the deck in front

of each switchboard and, if the switchboard is accessible from the rear, on the deck behind the switchboard.

(h) Each uninsulated current-carrying part must be mounted on non-combustible, nonabsorbent, high-dielectric insulating material.

(i) Equipment mounted on a hinged door of an enclosure must be constructed or shielded so that no person will come into accidental contact with energized parts of the door-mounted equipment when the door is open and the circuit energized.

(j) Bus capacity of switchboards and main distribution panels must be sized in accordance with §111.30-19(a) of this chapter. Panelboards must have current rating of not less than the feeder-circuit capacity.

§ 129.340 Cable and wiring.

(a) If individual wires, rather than cables, are used in systems operating at a potential of greater than 50 volts, the wire and associated conduit must be run in a protected enclosure. The protected enclosure must have drain holes to prevent the buildup of condensation.

(b) Each cable and wire must—

(1) Have stranded copper conductors with sufficient current-carrying capacity for the circuit in which it is used;

(2) Be installed so as to avoid or reduce interference with radio reception and compass indication;

(3) Be protected from the weather;

(4) Be supported so as to avoid chafing or other damage;

(5) Be installed without sharp bends;

(6) Be protected by metal coverings or other suitable means, if in areas subject to mechanical abuse;

(7) Be suitable for low temperature and high humidity, if installed in refrigerated compartments;

(8) Be located outside a tank, unless it supplies power to equipment in the tank; and

(9) Have sheathing or wire insulation compatible with the fluid in a tank, when installed to comply with paragraph (b)(8) of this section.

(c) Cable and wire in power and lighting circuits must be #14 AWG or larger. Cable and wire in control and indicator circuits must be #22 AWG or larger, or be ribbon cable or similar, smaller,