

(c) The circuit breaker of a generator not to be operated in parallel with another generator must be interlocked to prevent that generator from being connected to the switchboard simultaneously with another.

§ 129.326 Dual-voltage generators.

If a dual-voltage generator is installed on an OSV—

(a) The neutral of the dual-voltage system must be solidly grounded at the switchboard's neutral bus and be accessible for checking the insulation resistance of the generator; and

(b) Ground detection must be provided that—

(1) For an alternating-current system, complies with §111.05-27 of this chapter; and

(2) For a direct-current system, complies with §111.05-29 of this chapter.

§ 129.330 Distribution panels and switchboards.

(a) Each distribution panel or switchboard must be in a location as dry as practicable, accessible, adequately ventilated, and protected from falling debris and dripping or splashing water.

(b) Each distribution panel or switchboard must be totally enclosed and of the dead-front type.

(c) Each switchboard must have non-conductive handrails.

(d) Each switchboard or main distribution panel must be fitted with a dripshield, unless the switchboard or distribution panel is of a type mounted deck-to-overhead and is not subject to falling objects or liquids from above.

(e) Each distribution panel and switchboard accessible from the rear must be constructed to prevent a person's accidental contact with energized parts.

(f) Working space must be provided around each main distribution panel and switchboard of at least 610 millimeters (24 inches) in front of the switchboard and, of at least 460 millimeters (18 inches) from the nearest bulkhead, stiffener, or frame behind the switchboard. Rear access is prohibited when the working space behind the switchboard is less than 460 millimeters (18 inches).

(g) Nonconductive mats or grating must be provided on the deck in front

of each switchboard and, if the switchboard is accessible from the rear, on the deck behind the switchboard.

(h) Each uninsulated current-carrying part must be mounted on non-combustible, nonabsorbent, high-dielectric insulating material.

(i) Equipment mounted on a hinged door of an enclosure must be constructed or shielded so that no person will come into accidental contact with energized parts of the door-mounted equipment when the door is open and the circuit energized.

(j) Bus capacity of switchboards and main distribution panels must be sized in accordance with §111.30-19(a) of this chapter. Panelboards must have current rating of not less than the feeder-circuit capacity.

§ 129.340 Cable and wiring.

(a) If individual wires, rather than cables, are used in systems operating at a potential of greater than 50 volts, the wire and associated conduit must be run in a protected enclosure. The protected enclosure must have drain holes to prevent the buildup of condensation.

(b) Each cable and wire must—

(1) Have stranded copper conductors with sufficient current-carrying capacity for the circuit in which it is used;

(2) Be installed so as to avoid or reduce interference with radio reception and compass indication;

(3) Be protected from the weather;

(4) Be supported so as to avoid chafing or other damage;

(5) Be installed without sharp bends;

(6) Be protected by metal coverings or other suitable means, if in areas subject to mechanical abuse;

(7) Be suitable for low temperature and high humidity, if installed in refrigerated compartments;

(8) Be located outside a tank, unless it supplies power to equipment in the tank; and

(9) Have sheathing or wire insulation compatible with the fluid in a tank, when installed to comply with paragraph (b)(8) of this section.

(c) Cable and wire in power and lighting circuits must be #14 AWG or larger. Cable and wire in control and indicator circuits must be #22 AWG or larger, or be ribbon cable or similar, smaller,