

§ 111.15-25

discharge current, whichever is greater, while maintaining the proper voltage at the load end.

[CGD 94-108, 61 FR 28278, June 4, 1996, as amended at 62 FR 23908, May 1, 1997]

§ 111.15-25 Overload and reverse current protection.

(a) An overload protective device must be in each battery conductor, except conductors of engine cranking batteries and batteries with a nominal potential of 6 volts or less. For large storage battery installations, the overcurrent protective devices must be next to, but outside of, the battery room.

(b) Except when a rectifier is used, the charging equipment for all batteries with a nominal voltage more than 20 percent of line voltage must protect automatically against reversal of current.

§ 111.15-30 Battery chargers.

Each battery charger enclosure must meet § 111.01-9. Additionally, each charger must be suitable for the size and type of battery installation that it serves. Chargers incorporating grounded autotransformers must not be used. Except for rectifiers, chargers with a voltage exceeding 20 percent of the line voltage must be provided with automatic protection against reversal of current.

[CGD 94-108, 61 FR 28278, June 4, 1996; 61 FR 36787, July 12, 1996]

Subpart 111.20—Transformer Construction, Installation, and Protection

§ 111.20-1 General requirements.

Each transformer winding must be resistant to moisture, sea atmosphere, and oil vapor, unless special precautions are taken, such as enclosing the winding in an enclosure with a high degree of ingress protection.

[CGD 94-108, 61 FR 28278, June 4, 1996]

§ 111.20-5 Temperature rise.

(a) The temperature rise, based on an ambient temperature of 40 degrees C, must not exceed the following:

46 CFR Ch. I (10-1-02 Edition)

(1) For Class A insulation, 55 degrees C.

(2) For Class B insulation, 80 degrees C.

(3) For Class F insulation, 115 degrees C.

(4) For Class H insulation, 150 degrees C.

(b) If the ambient temperature is higher than 40 degrees C, the transformer must be derated so that the total temperature stated in this section is not exceeded. The temperature must be taken by the resistance method.

§ 111.20-10 Autotransformers.

An autotransformer must not supply feeders or branch circuits.

§ 111.20-15 Transformer overcurrent protection.

Each transformer must have protection against overcurrent that meets article 450 of the NEC or IEC 92-303.

[CGD 94-108, 61 FR 28278, June 4, 1996]

Subpart 111.25—Motors

§ 111.25-1 General requirements.

The requirements for generators contained in § 111.12-5 apply to motors.

[CGD 74-125A, 47 FR 15236, Apr. 8, 1982, as amended by CGD 94-108, 62 FR 23908, May 1, 1997]

§ 111.25-5 Marking.

(a) Each motor must have a marking or nameplate that meets either article 430-7 of the NEC or IEC 92-301 (clause 16).

(b) The marking or nameplate for each motor that is in a corrosive location must be corrosion-resistant.

[CGD 74-125A, 47 FR 15236, Apr. 8, 1982, as amended by CGD 94-108, 61 FR 28278, June 4, 1996]

§ 111.25-15 Duty cycle.

Each motor must be rated for continuous duty, except a motor for an application listed in Table 111.25-15 or a similar duty must meet the minimum short-time rating stated in the table.