

(2) A pilot light connected to the shore side of the circuit breaker or fused switch; and

(3) One of the voltmeters under paragraph (b)(5) of this section connected to show the voltage of each phase of the shore power connection.

(g) The equipment under paragraphs (b), (d), (e), and (f) of this section, except the equipment under paragraphs (b)(1), (b)(2), and (f)(1), must be on the ship's service switchboard or on a central control console that:

(1) Is in the same control area as the main ship's service switchboard or can remotely control the ship's service generator circuit breaker;

(2) Has a generator section that has only generator functions;

(3) Has the generator section segregated from each other console section by a fire-resistant barrier; and

(4) Has cabling from the main switchboard to the generator section of the console that:

(i) Has only generator control and generator instrumentation circuits; and

(ii) Is protected from mechanical damage.

§ 111.30-27 Direct current ship's service switchboards.

(a) Each direct current ship's service switchboard must have the equipment required by paragraphs (b) through (f) of this section.

(b) For each connected generator, each switchboard must have the following:

(1) A circuit breaker that meets § 111.12-11 and § 111.50-5.

(2) A disconnect switch or link for each generator conductor, except a switchboard having a draw-out or plug-in type generator circuit breaker that disconnects—

(i) Each conductor; or

(ii) If there is a switch in the generator neutral, each ungrounded conductor.

(3) A field rheostat.

(4) A pilot lamp connected between the generator and circuit breaker.

(c) For each two-wire generator, each switchboard must have:

(1) An ammeter; and

(2) A voltmeter with a selector switch that connects the voltmeter to show:

(i) Generator voltage; and

(ii) Bus voltage.

(d) For each three-wire generator, each switchboard must have the following:

(1) An ammeter for:

(i) The positive lead; and

(ii) The negative lead.

(2) A center zero type ammeter for the neutral ground connection.

(3) A voltmeter with a selector switch that connects the voltmeter to show generator and bus voltage:

(i) Positive to negative;

(ii) Positive to neutral; and

(iii) Neutral to negative.

(e) Each switchboard must have ground detection that meets Subpart 111.05 for the:

(1) Main power system;

(2) Main lighting system; and

(3) Emergency lighting system.

(f) For each shore power connection, each switchboard must have:

(1) A circuit breaker or fused switch; and

(2) A pilot light connected to the shore side.

(g) One of the voltmeters under paragraph (c)(2) or (d)(3) of this section must be connected to show:

(1) For each two-wire system, shore connection voltage; and

(2) For each three-wire system, shore connection voltage:

(i) Positive to negative;

(ii) Positive to neutral; and

(iii) Neutral to negative.

§ 111.30-29 Emergency switchboards.

(a) Each emergency generator must have an emergency switchboard.

(b) There must be a test switch at the emergency switchboard to simulate a failure of the normal power source and cause the emergency loads to be supplied from the emergency power source.

(c) The emergency switchboard must be as near as practicable to the emergency power source but not in the same space as a battery emergency power source.

(d) Each alternating-current emergency switchboard must have the